

GGT-30 Geophysical Transmitter

High Power and Fast Turn-off



FEATURES

- Constant current supply
- Used for time/frequency domain IP, Resistivity, CR, TEM, FEM, CSAMT
- Broad-band: DC to 8 kHz (standard)
- Output up to 1000 V, 45 A
- Fast turn-off time: 125 μ sec (300 x 300 m loop)
- Drives a loop or grounded dipole
- Efficient, modular design
- Rugged design reliable in all climates

SPECIFICATIONS FOR THE GGT-30 TRANSMITTER

General

Description: Broadband, constant-current, time and frequency domain, high-power geophysical transmitter

Enclosure: Welded, hardened aluminum frame with removable side panels, non-conducting paint

Size: 78 x 46 x 45 cm (31 x 18 x 18 in)

Weight: 93 kg (205 lb)

Operating temperature: -40° to +55°C (-40° to +130°F)

Operating humidity: 0 to 90%, non-condensing

Electrical Characteristics

Drives a loop or grounded dipole

Turnoff time: Under 10 μ sec for a resistive load; 125 μ sec for a 300 x 300 m loop (16 ohms resistance, full current)

Maximum input: 30KVA @ 30°C

Output voltage range: 50 to 1000V

Output current range: 0.2 to 45A

Current stability: \pm 0.2%

Frequency range: DC to 8 kHz

Switching Control

Switching controlled by external device

Recommended transmitter controller:
Zonge XMT-32

Waveform type: Capable of virtually any type of pulse waveform, limited by external controller device

Controls

Power ON / OFF

Transmit / Reset switch

Current adjust pot, continuously adjustable, locking

Voltage range switch (50-250V, 200-500V, 450-750V, 700-1000V)

Loop / Dipole select switch

Displays

Analog input voltage meter, 0-150 V

Analog output voltage meter, 0-1000 V

Power On / Off lamp, transmit lamp, output lamp

Selectable LCD meter:

Output current (\pm 0.01A)

Input power (0-30 KW)

Transformer temperature

Loop turnoff time (microseconds)

Indicator lamps: control power on, transmit on, transmit polarity

Fault indicator lamps: output and input overcurrent, output and input overvoltage, end of regulation, alternator overvoltage, open circuit

Output Jacks

Current calibrate terminals (50 mV/A)

Output current terminals

Grounding jack

Power

Three-phase, 120 VAC, 400 Hz

Recommended motor generator set:

Zonge ZMG-30

Power connector: four-pin military screw-type with locking ring

Options

Spare parts kit (standard and extended kits available)

LCD heater for temperatures below -15°C (+5°F)

Current monitor isoamp module

Resistor load bank

Switch box for rapid switching of dipole pairs

*Specifications subject to change without notice
© Copyright 2013, Zonge International, Inc.*

Zonge Offices:

Arizona, Alaska, Nevada, Colorado and Oregon

Headquarters:

3322 E. Ft. Lowell Road, Tucson, AZ 85716, USA (800) 523-9913

Tel: (520) 327-5501 Email: zonge@zonge.com

Fax: (520) 325-1588 Web: <http://www.zonge.com>

20130122